Gigaset A680/A685

Handset

1 Charge status of the batteries
2 Answer machine icon (A685 only)
3 Display keys
4 Message key
Flashes: new messages received
5 Handsfree key
6 Control key ([▲▼])
7 Talk key
8 Directory key (press down on the control key)
9 End call key and On/Off key
10 Ringer tone on/off (press and hold in idle status)
11 Keypad lock on/off (press and hold)
12 Recall key
- Consultation call (flash)
- Dialling pause (press and hold)
13 Microphone
14 Alarm clock key



Base station

Registration/Paging key (page 10)

Display keys:

Pressing a key launches the function that appears above that key in the display.

Display	Function when pressed
INT	Call other registered handsets page 10.
MENU	Open main/submenu (see Menu tree page 19).
↩	Go back one menu level.
▲▼	Scroll up/down or adjust volume with [▲▼].
◀▶	Move cursor to left/right with [▲▼].
◀C	Backspace deletes one character at a time.
OK	Confirm menu function or save entry.

Where to find it all

First steps ➔ page 3
Making calls ➔ page 7
Using the directory and lists ➔ page 7
Operating the answer machine (A685) ➔ page 9
Registering handsets ➔ page 10
Using several handsets ➔ page 10
Setting the alarm clock ➔ page 11
Phone settings ➔ page 11
Operating the base station on the PABX ➔ page 11
Menu tree ➔ page 19

Safety precautions

Read this user guide and the safety precautions carefully before use. Explain their contents and the potential hazards associated with using the telephone to your children.

Only use **the mains unit supplied**.

Fit only the **recommended, rechargeable batteries** (➔ page 12), i.e. never use a conventional (non-rechargeable) battery or other battery types as this could result in significant health risks and personal injury.

The operation of medical appliances may be affected. Be aware of the technical conditions in your particular environment, e.g. doctor's surgery.

Do not hold the rear of the handset to your ear when it is ringing. Otherwise you risk serious and permanent damage to your hearing.
The handset may cause an unpleasant humming noise in hearing aids.

Do not install the phone in a bathroom or shower room. The handset and base station are not splashproof.

Do not use your phone in environments with a potential explosion hazard, e.g. paint shops.

If you give your Gigaset to someone else, make sure you also give them the user guide.

Please remove faulty base stations from use or have them repaired by our service, as they could interfere with other wireless services.

Disposal
Batteries should not be disposed of in general household waste. Observe the local waste disposal regulations, details of which can be obtained from your local authority.
All electrical and electronic products should be disposed of separately from the municipal waste stream via designated collection facilities appointed by the government or the local authorities.
This crossed-out wheeled bin symbol on the product means the product is covered by the European Directive 2002/96/EC..
The correct disposal and separate collection of your old appliance will help prevent potential negative consequences for the environment and human health. It is a precondition for reuse and recycling of used electrical and electronic equipment.
For more detailed information about disposal of your old appliance, please contact your local council refuse centre or the original supplier of the product.

Emergency numbers cannot be dialled if the keypad lock (➔ page 1) is activated!
Not all of the functions described in this user guide are available in all countries.

Care

Wipe down the base station and handset with a **damp** cloth (no solvents) or an antistatic cloth. **Never** use a dry cloth. This can cause static.

Contact with liquid ⚠

If the handset should come into contact with liquid:

- **Switch the handset off and remove the batteries immediately.**
- Allow the liquid to drain from the handset.
- Pat all parts dry, then with the battery compartment open and the keypad facing down place the handset in a dry, warm place **for at least 72 hours** (**not** in a microwave, oven etc.).
- **Do not switch on the handset again until it is completely dry.**

When it has fully dried out, you will normally be able to use it again.

ECO WDCT

You are helping to protect the environment with your Gigaset A680/A685.

Reduced energy consumption

Your telephone has an energy-saving adapter plug and uses less energy.

Reduced transmission power

The transmission power of your telephone is reduced **automatically**:

- The transmission power **on the base station** is reduced to virtually zero when only one handset is registered and the handset is in the base station.

First steps

Check the pack contents

- One Gigaset A680/A685 base station,
- one mains adapter,
- one Gigaset A68H handset,
- one phone cord,
- two batteries,
- one battery cover,
- one user guide.

If you have purchased a **model with multiple handsets**, the package should contain two batteries, a battery cover and a charging cradle with mains adapter for each additional handset.

Setting up the base station and charging cradle (if included)

The base station and charging cradle are designed for use in enclosed dry rooms with a temperature range of +5 °C to +45 °C.

- Set up the base station at a central location on a flat, non-slip surface in your house or apartment.

Please note

Pay attention to the range of the base station.
This is up to 300 m in unobstructed outdoor areas and up to 50 m inside buildings.

The phone's feet do not usually leave any marks on surfaces. However, due to the multitude of different varnishes and polishes used on today's furnishings, the occurrence of marks on the surfaces cannot be completely ruled out.

Please note:

- Never expose the telephone to the influence of heat sources, direct sunlight or other electrical devices.
- Protect your Gigaset from moisture, dust, corrosive liquids and vapours.

Connecting the base station

- **First** connect the mains adapter 1.
- **Then** connect the telephone jack 2 and insert the cables into the cable ducts.



Please note:

- The mains adapter must **always be connected**, as the phone will not operate without mains connection.
- Only use the mains adapter and phone cord **supplied**. Pin connections on telephone cables can vary.

Connecting the charging cradle (if included)



- Connect the flat plug from the power supply 1.
- Plug the mains adapter into the plug socket 2.



If you need to disconnect the plug from the charging cradle, press the release button 1 and disconnect the plug 2.

Setting up the handset for use



The display is protected by a plastic film.
Please remove the protective film!

Inserting the batteries and closing the battery cover

Warning

Use only the rechargeable batteries recommended by Gigaset Communications GmbH (→ page 12). Never use a conventional (non-rechargeable) battery or other battery types as this could result in significant health risks and personal injury. For example, the batteries could explode. The phone could also malfunction or be damaged as a result of using batteries that are not of the recommended type.

- Insert the batteries the right way round.
  The polarity is indicated in/on the battery compartment.



- First insert the battery cover at the top ⓐ.
- Then press the cover ⓑ until it clicks into place.

If you need to open the battery cover, for instance to replace the batteries, place your fingertip in the cavity on the casing and pull the battery cover upwards.

Placing the handset in the base station and registering

Register HS
MENU

Before you can use the phone, you must first register the handset to the base station.

▶ Place the handset with the **display facing up** in the base station.

Registering

The handset registers automatically. Registration can take **up to 5 minutes**.
Do not remove the handset from the base station during this time.

INT MENU

After successful registration, the idle screen is displayed.
Charge status of the batteries:

- (flat to full)
- flashes: batteries almost flat
- flashes: charging

If you have purchased a **model with multiple handsets**, repeat the registration process for **each individual** handset. Handsets are assigned the lowest available internal number (1-4). If more than one handset is registered to the base station, the internal handset number appears in the top left of the display, e.g. 2. If the internal numbers 1–4 are already assigned to other devices, the number 4 will be overwritten.

Please note

- Each key press interrupts the automatic registration.
- If automatic registration does not work, the handset will have to be registered manually (➜ page 10).
- Only place the handset in the base station or charging cradle that is intended for it.

Initial charging and discharging of the batteries

The correct charge level can only be displayed if the batteries are first fully charged **and** discharged.

- Place the handset in the base station or charging cradle for **eight** hours.
- Then remove the handset from the base station or charging cradle and do not replace it until the batteries are completely discharged.

Please note

- After the first battery charge **and** discharge you may replace your handset in the base station or charging cradle after every call.
- Always repeat the charging and discharging procedure if you remove the batteries from the handset and reinsert them.
- The batteries may warm up during charging. This is not dangerous.
- After a while, the charge capacity of the batteries will decrease for technical reasons.

Setting the date and time

Set the date and time so that the correct date and time can be assigned to incoming calls, and so that the alarm can be used.

MENU ➔ **Settings** ➔ **OK** ➔ **Date/Time** ➔ **OK**
➔ **Date:** ➔ (enter the day, month and year in 6-digit format) ➔ **OK**
➔ **Time:** ➔ (enter hours and minutes in 4-digit format) ➔ **OK** (display message: **Saved**)
➔ (press and **hold** to return to idle status)

Please note

When entering the time and date, you can move the position of an entry to the left or right by pressing the control button up or down.

Display in idle status

Once the phone is registered and the time set, the idle display is shown as in this example.
If the answer machine is activated (A685), the answer machine icon will be displayed in the header. Your answer machine is set with a pre-recorded announcement.



Activating/deactivating the handset

Press and **hold** the key to activate or deactivate the handset.
If you place a deactivated handset in the base station or charging cradle, it will automatically activate.

Your phone is now ready for use.

If you have any questions about using your phone, please read the tips on troubleshooting ("Questions and answers" ➔ page 13) or contact our Customer Care team page 19.

Making calls

Making external calls and ending calls

External calls are calls using the public telephone network.

(Enter the phone number) ➜ .

The phone number is dialled. (Or you can **first** press and **hold** [dial tone] and then enter the number.)

During the call you can adjust the earpiece volume using and set the volume with .

End the call/cancel dialling:

Press the end call key .

You can automatically insert a network provider dialling code before any phone number (see Menu tree "Preselection" ➜ page 19).

Accepting a call

The handset indicates an incoming call by ringing and by a display on the screen.

Press the talk key to accept the call.

When **Auto Answer** is activated (see Menu tree ➜ page 19), simply remove the handset from the base station/charging cradle.

In idle status, use to activate the menu for setting the call volume and use to set the volume.

Calling Line Identification

When you get a call, the caller's number will be displayed on your handset; the caller's name will be displayed if it is stored in the directory.

Preconditions:

1. You have asked your network provider for the caller's number (CLIP) to be displayed on your handset screen.
2. The caller has asked the network provider for his number to be identified (CLI).

appears in the display if you have not requested Calling Line Identification, **Withheld** appears if the caller has withheld CLI, and **Unavailable** appears if CLI has not been requested.

Handsfree

Activating while dialling:

Enter the number and press the handsfree key .

Switching between earpiece and handsfree mode:

During a call and when listening to the answer machine (A685 only), press the handsfree key to activate or deactivate handsfree talking.

During a call, use to activate the menu for setting the handsfree volume and use to set the volume.

Using the directory and lists

Directory

To open the directory: press .

You can save up to 50 phone numbers (max. 32 digits) with corresponding names (max. 14 characters).

Enter letters/characters ➜ page 12.

Saving the first number in the directory

➜ **New Entry?** ➜ **OK**
➜ (enter number) ➜ **OK**
➜ (enter number) ➜ **OK**

Storing a number in the directory

➜ **MENU** ➜ **New Entry** ➜ **OK**
➜ (enter number) ➜ **OK**
➜ (enter number) ➜ **OK**

Selecting a directory entry

Open the directory with . You have the following options:

- Use to scroll through the entries until the required name is selected.
- Enter the first character of the name and scroll to the entry with , if required.

Dialling with the directory

➜ (select entry) ➜

Using other functions

➜ (select entry) ➜ **MENU**

The following functions can be selected with :

New Entry	Save new phone number.
Show Number	Display the phone number.
Use Number	Edit or add to the number. Then dial or use other functions with **MENU**.
Edit Entry	Edit selected entry.
Delete Entry	Delete selected entry.
Send Entry	Send a single entry to another handset (➜ page 8).
Delete List	Delete **all** directory entries.
Send List	Send the complete list to another handset (➜ page 8).
Shortcut	For shortcuts, assign the current entry to a key.

Setting the shortcut key

📖 ➔ **MENU** ➔ Scroll to **Shortcut** ➔ Scroll to select a number (0,2-9), for example: **Shortcut: 2** ➔ **OK**

Using shortcut keys

To dial, press and **hold** the required shortcut key.

Sending the directory to another handset

Preconditions:

- The sending and receiving handsets must both be registered to the same base station.
- The other handset and the base station can send and receive directory entries.

📖 ➔ (select entry) ➔ **MENU** ➔ **Send Entry** / **Send List** ➔ **OK** ➔ (enter the internal number of the receiving handset) ➔ **OK**

Last number redial list

This list contains the ten last dialled numbers.

Dialling from the last number redial list

✆ (**press** briefly) ➔ (select entry) ➔ ✆

Managing entries in the last number redial list

✆ (**press** briefly) ➔ (select entry) ➔ **MENU**

You can select the following settings:

Use Number	Edit or add to the number. Then dial or use other functions with **MENU**.
Copy to Dir.	Copy an entry to the directory.
Delete Entry	Delete selected entry.
Delete List	**Delete** all entries.

Calls list/answer machine (network mailbox) list

An advisory tone sounds and the message key flashes as soon as a **new entry** appears in the calls list/answer machine list. A message appears in the display.

When you press the ✉ key, all the lists are displayed. If only one list contains new messages, this will be opened automatically.

Please note:

If calls are saved in the network mailbox, you will receive a message if the appropriate settings have been made (depending on your network provider).

Calls list

Precondition: CLIP (➔ page 7)

The call list contains all incoming calls.

The calls list is displayed as follows:

```
CallsList 01+02
```

Number of new entries + number of old, read entries

Open the calls list

✉ ➔ **CallsList 01+02** ➔ **OK**

The last incoming call is displayed.

If necessary, use to select another entry.

Using other functions

(select entry) ➔ **MENU**

The following functions can be selected with :

Delete Entry	Delete current entry.
Copy to Dir.	Copy an entry to the directory.
Date/Time	Call date and time (if set).
Status	**New Call:** new missed call. **Old Call:** entry already read. **Answ.:** call taken.
Delete List	**Warning!** All **old and new** entries will be deleted.

Calling back a caller from the calls list

✉ ➔ **CallsList 01+02** ➔ **OK** ➔ (select entry) ➔ ✆

Answer machine list (A685 only)

You can use the answer machine list to listen to the messages that are on the answer machine.

The answer machine list is displayed as follows:

```
VoiceMail 01+02
```

Number of new messages + number of old, played back messages

Opening the answer machine list

✉ ➔ **VoiceMail 01+02** ➔ **OK**

If you have new messages, playback will start with the first new message, otherwise with the first old message.

Using other functions

(Select entry) ➔ **MENU**

The following functions can be selected with :

Continue	Resume paused playback.
Volume	Set the volume.
Copy to Dir.	Copy an entry to the directory.
Delete all old	Delete all old messages.

Operating the answer machine (A685)

The answer machine can be operated from the handset .
The telephone is supplied with a pre-recorded announcement. This pre-recorded announcement is used if no personal announcement is available.
If the memory is full, the answer machine switches itself off automatically. It activates again automatically when you delete old messages.

Activating/deactivating the answer machine

MENU ➔ Voice Mail ➔ OK ➔ Answer Mach. ➔ OK (✓ = on)

When you switch on the answer machine, the ⌾ icon appears in the display.

Recording your own announcement

MENU ➔ Voice Mail ➔ OK ➔ Announcements ➔ OK
➔ Rec announce ➔ OK ➔ Speak after OK ➔ OK

You hear the ready tone (short tone). Now speak your announcement (at least 3 sec.). Press **OK** to confirm or press ☎ or ⮌ to reject your recording. After recording, the announcement is played back for you to check.

Please note:

Recording ends automatically when the max. recording time of 170 seconds is reached or if there is a break in speaking of more than 2 seconds.

Playing back or deleting announcements

See Menu tree ➔ page 20.

Playing/deleting messages

Open the answer machine list to play back messages.

Stopping and controlling playback

During message playback:

2	Stop playback. Press **2** again to resume.
[▲]	Go to the start of the current message.
2 x [▲]	Skip to the previous message.
[▼]	Skip to the next message.
2 x [▼]	Skip ahead two messages.

Deleting individual messages

While playback is paused, press the ◂C display key.

Deleting all old messages

During playback or pause:

MENU ➔ Delete all old ➔ OK (Confirm the security prompt)

Picking up a call from the answer machine

You can still accept a call while the answer machine is recording the message by pressing ✆ . Recording stops and you can speak to the caller.

Setting up the answer machine

The answer machine has already been preset at the factory. Make individual settings using the handset.
Details on how to set a delay time, after which the answer machine is to answer a call, as well as details on how to set the recording length and activate call screening during the recording, are available from the Menu tree ➔ page 20.

Assigning key 1 for fast access to the answer machine (network mailbox)

Simply press and **hold** key **1** on the handset and you will be connected directly to the answer machine (network mailbox).
See Menu tree ➔ page 20.

Remote operation when on the move

You can check and activate your answer machine from any other telephone (hotel, pay phone etc.).

Preconditions:

- You have set a system PIN other than 0000 ➔ page 19.
- The phone you are using for remote operation has touch tone dialling (DTMF), i.e. you hear different tones when you press the keys.

Calling the answer machine and playing back messages

(Dial your own number) ➔ while listening to your announcement: press the [9] key and enter the system PIN

The following keys are used for operation:

[1]	Go to the start of the current message. Press twice to go back to the previous message.
[2]	Stop playback. Press again to resume.
[3]	Skip to next message.
[0]	Delete current message.

Activating the answer machine

(Enter your own number and allow the phone to ring until you hear the message: "Please enter PIN") ➜ enter system PIN

Your answer machine is activated. It tells you how much memory time is left. The messages are now played back. The answer machine cannot be deactivated remotely.

Locating a handset ("paging")

You can locate your handset using the base station.

- **Briefly** press the registration/paging key on the base station (➜ page 1).
- All handsets will ring simultaneously ("paging"), even if the ringer tones are deactivated.

End paging: briefly press the register/paging key on the base station (➜ page 1) or the talk key on a handset.

Registering handsets

You can register up to four handsets on your base station (Gigaset A68H) recommended).

Please note:

Each additional handset must be registered on the base station in order for it to work properly!

For automatic registration of handsets to Gigaset A680/A685, see ➜ page 5.

Manual registration of handsets to Gigaset A680/A685

1. On the handset: MENU ➜ Settings ➜ OK ➜ Handset ➜ OK ➜ Register HS ➜ Enter the system PIN of the base station (default is 0000) **➜ OK.**

Registering flashes in the display.

2. On the base station: within **60 sec.** of entering the system PIN, press and hold the registration/paging key (➜ page 1) (min. 3 sec.).

Registration takes approx. 1 minute.

De-registering handsets

Handsets can only be de-registered by resetting the base station to its default settings. **This will also reset every other setting** ➜ page 11**.**

If you have **only** registered handsets for other GAP-compatible devices, these can only be de-registered with a **hardware reset** ➜ page 11.

Using several handsets

Making internal calls

Internal calls are no-cost calls to other handsets that are registered to the same base.

Press the **INT** display key. All handsets are called.

When an internal participant answers you can speak to them. To end the call, press ☎.

Internal consultation call/connecting a call

You are in conversation with an **external** participant. Press the **INT** key to call all handsets. The external participant hears the hold music.

- **Before** the internal participant has answered, press the end call key ☎; the call is diverted to the participant who answers the call.
- **After** the internal participant has answered, you can talk to him. Press the end call key ☎; the call is diverted, **or** press the display key ⮌; you are reconnected to the external participant.

Listening in to an external call

You are conducting an external call. An internal participant can listen in on this call and take part in the conversation (conference).

Precondition: The **Listening in** function must be activated.

Activating/deactivating listening in

MENU ➜ Settings ➜ OK ➜ Base ➜ OK ➜ Listening in ➜ OK (✓ = on)

Internal listening in (conference)

You want to listen in to an existing external call.

Briefly press and **hold** the key. You can listen in to the call. All participants hear a signal tone.

To end: press the end call key ☎. All participants hear a signal tone.

If the **first** internal participant presses the end call key ☎, the handset that has "listened in" remains connected to the external participant.

Setting the alarm clock

Activating/deactivating the alarm clock

MENU ➜ **Alarm Clock** ➜ **OK** ➜ **Activation** ➜ **OK** (✓ = on)

or:

press the alarm clock key ⏲

When activated:

➜ Set the wake-up time ➜ **OK**

When the alarm clock rings, press any key to switch it off for 24 hours. If the alarm clock is set, the wake-up icon ⏰ will appear on the screen and the wake-up time will be displayed instead of the date.

Setting the wake-up time

MENU ➜ **Alarm Clock** ➜ **OK** ➜ **Wake-up time** ➜ **OK**

Enter the wake-up time in hours and minutes, then press **OK**.

Phone settings

For details on how to make audio settings, see Menu tree ➜ page 19.
For details on how to set the system PIN on the base station, see the Menu tree ➜ page 19.

Resetting the handset

You can reset individual settings and changes that you have made. Entries in the directory, the calls list and the handset's registration to the base station will be retained.

MENU ➜ **Settings** ➜ **OK** ➜ **Handset** ➜ **OK** ➜ **Reset Handset** ➜ **OK**

Cancel the reset with ☎.

Restoring the base station to the factory settings

When restoring factory settings:

- All handsets are de-registered
- Individual settings are reset
- All lists are deleted
- The system PIN is reset to the original code **0000**

Only the date and time are retained.

Software reset

MENU ➜ **Settings** ➜ **OK** ➜ **Base** ➜ **OK** ➜ **Base Reset** ➜ **OK**

Hardware reset

Disconnect the power cord from the base station. Hold down the registration/paging key (➜ page 1) on the base station while reconnecting the power cable to the base station. Release the key after approximately 5 seconds.

Operating the base station on the PABX

The following settings are only necessary when your PABX requires them, see the user guide for your PABX. When entering the digits, enter them **slowly** one after the other.

Changing the dialling mode

MENU ➜ **3 3 9 1 1** ➜ The number for the set dialling mode flashes: **0** = touch tone dialling (DTMF); **1** = dial pulsing (DP) ➜ enter number ➜ **OK**.

Setting recall

MENU ➜ **3 3 9 1 2** ➜ The number for the current recall flashes: **0** = 80 ms; **1** = 100 ms; **2** = 120 ms; **3** = 400 ms; **4** = 250 ms; **5** = 300 ms; **6** = 600 ms; **7** = 800 ms ➜ enter number ➜ **OK**.

Changing pause after line seizure

You can set the length of the pause inserted between pressing the talk key ✆ and sending the phone number.

MENU ➜ **3 3 9 1 9** ➜ The number for the current pause length flashes: **1** = 1 sec.; **2** = 3 sec.; **3** = 7 sec. ➜ enter number ➜ **OK**.

Changing the pause after the recall key

MENU ➜ **3 3 9 1 4** ➜ The number for the current pause length flashes: **1** = 800 ms; **2** = 1600 ms; **3** = 3200 ms ➜ enter number ➜ **OK**.

Appendix

Entering letters/characters

Press the relevant key the number of times indicated. **Briefly** press the hash key # to switch from "Abc" to "123" mode, from "123" to "abc"mode and from "abc" to "Abc" mode.

Standard characters

	1x	2x	3x	4x	5x	6x	7x	8x	9x	10x	11x	12x	13x	14x
1	␣ 1)	1	£	$	¥	¤								
2	a	b	c	2	ä	á	à	â	ã	ç				
3	d	e	f	3	ë	é	è	ê						
4	g	h	i	4	ï	í	ì	î						
5	j	k	l	5										
6	m	n	o	6	ö	ñ	ó	ò	ô	õ				
7	p	q	r	s	7	ß								
8	t	u	v	8	ü	ú	ù	û						
9	w	x	y	z	9	ÿ	ý	æ	ø	å				
0	.	,	?	!	0	+	-	:	¿	¡	"	’	;	_
*	*	/	(	)	<	=	>	%						
#	Abc -> 123	123 -> abc	#	@	\	&	§							

1) Space

Specifications

Recommended batteries

Technology: Nickel-metal-hydride (NiMH)
Size: AAA (Micro, HR03)
Voltage: 1.2 V
Capacity: 400–800 mAh

We recommend the following types of battery:

- GP 550/700 mAh
- Yuasa Phone 700/800 mAh
- Peacebay 550/650 mAh

(Valid at the time of going to press)

The handset is supplied with recommended batteries.

Base station power consumption

In standby mode – Handset in base station – Handset outside base station	 approx. 1.3 W approx. 1.3 W
During a call	approx. 1.5 W

General specifications

WDCT standard	is supported
No. of channels	80 duplex channels
Radio frequency range	2400-2483.5 Mhz
Duplex method	Time multiplex, 10 ms frame length
Bit rate	576 kbit/s
Modulation	GFSK
Transmission power	25 mW, average power per channel
Range	up to 300 m outdoors up to 50 m indoors
Base station power supply	230 V ~/50 Hz
Environmental conditions in operation	+5 °C to +45 °C; 20% to 75% humidity
Dialling mode	DTMF (touch tone dialling)/ DP (dial pulsing)

Questions and answers

If you have any queries about the use of your phone, you can contact us any time at www.gigaset.com/customercare.

The table below contains a list of common problems and possible solutions.

Problem	Cause	Solution
Nothing appears in the display.	The handset is not switched on. The batteries are flat.	Press the end call key ☎ for **approx. 5 seconds** or place the handset in the base station. Charge or replace the batteries.
No wireless connection to the base station, **Base** flashes in the display.	The handset is outside the range of the base station. The handset is not registered. The base station is not turned on.	Move the handset closer to the base station. Register the handset → page 10. Check the mains connector on the base station → page 3.
You cannot hear a ringer/ dialling tone from the fixed line network.	The phone cord supplied has not been used or has been replaced by a new cord with the wrong jack connections.	Please always use the phone cord supplied or ensure that the pin connections are correct when purchasing from a retailer: 3-4 assignment of telephone leads/ EURO CTR37.
Error tone sounds after system PIN prompt. PIN forgotten.	The system PIN you have entered is incorrect.	Reset the system PIN to the default 0000 → page 11. **All handsets are de-registered. All settings are reset. All lists are deleted.**

Customer Service & Assistance

Do you have any questions? As a Gigaset customer, you can find help quickly in this User Manual and in the service section of our Gigaset online portal www.gigaset.com/service.

In our constantly updated online service you can find:

- Extensive information about our products
- FAQ compilations
- Keyword search to help find topics quickly
- Compatibility database: Find out which base stations and handsets can be combined.
- Product comparison: Compare the features of several products with each other.
- Downloads for user manuals and current software updates
- E-mail contact form for customer service

Please register your phone online right after purchase.

This enables us to provide you with even better service regarding questions or an after sales query/ issue/claim. In order to contact our customer service via email, please use the email contact form from our Gigaset online portal after selecting your home country.

Our representatives are also available on the telephone hotlines for consultation.

Product warranty

Congratulations

On the purchase of your new Gigaset product, we guarantee that this equipment is a genuie manufacturer's product and extend the following warranty:

We guarantee this product against manufacturing defects for two full years from the date of purchase, unless specified otherwise.

Adaptors and batteries for cordless phones carry 6 months warranty from the date of purchase.

Gigaset Communications authorized Service Centres will replace or repair, if necessary, any defective part/parts free of charge by presenting this certificate of warranty at the Service Centre mentioned overleaf.

Warranty

1. This Certificate of warranty does not apply if the telephone has:
2. Been misused, mishandled, willfull damaged, neglected, damaged by lightning, improperly repaired, tested, altered improperly in any way.
3. A defect arising out of any failure to follow instructions either in the manual or product specification.
4. In case repairs are carried out of by unauthorized personnel or unauthorized source warranty will be void.
5. A defect arising from using non-Gigaset approved accessories or ancillary items attached to or in connection with the telephone.
6. If this certificate of warranty is not signed and stamped by the authorised distributor.
7. Any other claim resulting out of or in connection with the device shall be excluded from this warranty.

Certificate of warranty

The warranty is not valid if it is not signed and stamped by the authorized distributor.

Please fill in the following details and stamp the card to calidate the warranty. All details must be filled in by the dealer and retained by the Customer. The purchase receipt shall be required as evidence for invoking the warranty.

Customer's Name: _____

Product / Model: _____

Dealer's Name: _____

Date of Purchase: _____

Invoice / Cash Memo No./Date: _____

- Ownership of devices or components replaced by and returned Gigaset communications shall vest in Gigaset communications.
- This warranty shall apply to 2.4Ghz products purchased in India only.

Dealer's Stamp

Service Centres

We offer you support that is fast and tailored to your specific needs!

Our Online Support on the Internet:
www.gigaset.com/customercare

In some countries repair and replace services are impossible where the products are not sold through our authorised dealers.

Service Centres

Ahmedabad - inTarvo Technologies Limited

1st Floor, Rituraj Complex, 84/B, Swastik Society,Near Swastik Cross Roads, Navrangpura Ahmedabad - 380 009, Gujarat

Mr. Alpesh Rabari

Phone: 079-65499327

E-mail: setl.ahm@intarvo.com

Bangalore - inTarvo Technologies Limited

6/A, AVS Compound, Ijipura, 80 ft Road, Koramangala, Bangalore - 560 034, Karnataka

Mr. Harish

Phone: 080-41312700

E-mail: rtoebl.bangalore@intarvo.com

Baroda - inTarvo Technologies Limited

Shop No.10-11, Ground Floor, Profit Center, Kalaghoda, Syajigunj, Baroda - 390 005, Gujarat

Mr. Rakesh Agrawal

Phone: 0265-3911106

E-mail: sewd.baroda@intarvo.com

Chennai - inTarvo Technologies Limited

No: 112, 1st Floor, Vairam Complex, Thyagaraya Road, T.Nagar, Chennai - 600 017, Tamil Nadu

Mr. Deepa Balajee

Phone: 044-43412292

E-mail: deepa.balajee@intarvo.com

Delhi - inTarvo Technologies Limited

G4, 5, 6 Chandra Bhawan Nehru Place, New Delhi - 110 019

Mr.Meenakshi

Phone: 011-41095840

E-mail: se.np@intarvo.com

Gurgaon - inTarvo Technologies Limited

12, 13, 14, First Floor, Ganpati Complex, Old Delhi Road, Opp Hudda Nersury, Near Kataria Chowk, Gurgaon - 122 001, Harayana

Mr. Bhasker Patni

Phone: 0124-4286829 / -4286830

E-mail: bhasker.patni@intarvo.com

Hyderabad - inTarvo Technologies Limited

Sangeeta Plaza, No 3-9-241, 1st Floor, Near Police Station, West Marredpally, Secunderabad - 500 026, Andhra Pradesh

Mr. Narendra

Phone: 040-40072514

E-mail: csothers.hyd@intarvo.com

Kochi - Bits N Bytes Computers

No.43/1821 A, Post Office Building, S.R.M Road, Pachalam, Cochin, Kerala - 682 012

Mr. Shalu Thomas/Ms. Jinny

Phone: 9847401718 / 9744705512

E-mail: jinny.bits@gmail.com / microworldchn@vsnl.net

Kolkata - inTarvo Technologies Limited

2 Ripon Street, Near Hira International Hotel, Kolkata - 700 016, West Bengal

Mr. Surjit Dhar

Phone: 033-22277892/899

E-mail: se.east@intarvo.com

Ludhiana - inTarvo Technologies Limited

2nd Floor Madhok Complex, Ferozepur Road, Ludhiana - 141 003, Punjab

Mr. Manpreet Kaur

Phone: 0161-5081043

E-mail: se.ludhiana@intarvo.com

Mumbai - inTarvo Technologies Limited

First Floor, Hitech Plaza, Near MIDC office, Shanti nagar, Mahakali,Caves Road, Andheri (E) 400069, Mumbai

Mr. Kiran Chaudhary

Phone: 022-41224402

E-mail: kiran.chaudhary@intarvo.com

Nasik - inTarvo Technologies Limited

Viraj Corner, 2nd Floor, Shop No-9, Near India Bull, Opp BSNL Office, Sharanpur Road, Canada Corner, Nasik - 422 001, Maharshtra

Mr. Gopichand A. patil

Phone: (0253) 3024014

E-mail: sewd.nashik@intarvo.com

Noida - inTarvo Technologies Limited

C-32, First Floor, SECTOR-2, Near Hotel Nirula, Noiada - 201 301, Uttar Pradesh

Ms. Sudhir

Phone: 0120-4318632

E-mail: rcd.noida@intarvo.com

Pune - inTarvo Technologies Limited

"Shubham", 858, Dastur Meher Road, Near To Old Dorabji & Sons Hotel, Camp Pune - 411 001, Maharashtra

Mr. Savita Pardeshi

Phone: 020-41255792

E-mail: se.pune@intarvo.com

Rajkot - inTarvo Technologies Limited

RT Outsourcing Services Ltd - Rajkot,1 ST FLOOR PRTIBHA COMPLEX NEAR MAHASAGER TRAVELS MOTI TANKI CHOWK Rajkot – 360001

Mr. Ajit Nay

Phone: 0281-3049872/3054819/20

E-mail: se1.rajkot@rteservices.com

Surat

S.P Connecting

SEES, Shiv Pooja Point, Opp Turning point , Ghoddod road, Surat - 395002

Mr.Rushi Popat

Phone: 2612660552/ 9879133662

E-mail: sonyericsson.surat@yahoo.com

Vijayawada - Sigma Technologies

40-5-19/4A Lakshman's Enclave, Tikkle Road, Vijayawada - 520 010, Andhra Pradesh

Mr.Ravikumar Khammampalli

Phone: 9246472168

E-mail: customercare@sigmatechnologies.info

Vizag - Planet Solutions

KhammampalliC/o. S.N.K. IT Solutions Pvt. Ltd., D.No: 50-12-7/2, First Floor, Satya Residency, Seethammapeta, 530 016 Visakhapatnam

Mr. Srinivas Emula

Mr. K. Somu Naidu

Phone: 97044-80006 / 92466-45999

E-mail: aishplanet@gmail.com / snk-vizag@gmail.com

Menu tree

Your phone has an extensive range of features. These are offered in the form of menus.
To select a function while the phone is in **idle status**, press **MENU** (open menu), use the ▲ and ▼ keys to scroll to the function you require and press **OK** to confirm.

To return to idle status: press and hold the ☎ key.
As an alternative to selecting functions using the ▲ and ▼ buttons, you can also enter the digit combination that is in front of the function in the menu tree.
For setting the time and date, for example:
MENU ➔ 3 1 ➔ OK

1 Alarm Clock

1-1	Activation	Activating/deactivating the alarm clock
1-2	Wake-up time	Input format: HHMM

2 Audio Settings

2-1	Ringer Volume	5 levels + "crescendo" available		
2-2	Ringer Melody	2-2-1	External Calls	10 ringer tones available for external calls
		2-2-2	Internal Calls	10 ringer tones available for internal calls
		2-2-3	Alarm Clock	10 ringer tones available for alarm clock
2-3	Advis. Tones	During a conversation		
2-4	Battery Low	2-4-1	Off	Warning tone to indicate battery is almost flat: never
		2-4-2	On	always
		2-4-3	During Call	only during a call

3 Settings

3-1	Date/Time	Enter date (DDMMYY format), then time (HHMM format)		
3-2	Handset	3-2-1	Language	Set the display language
		3-2-2	Auto Answer	Automatically activate/deactivate auto answer ➔ page 7
		3-2-3	Register HS	Manually register the handset ➔ page 10
		3-2-4	Reset Handset	Reset the handset ➔ page 11
3-3	Base	3-3-1	System PIN	Change system PIN (default is 0000)
		3-3-2	Base Reset	Restore factory settings ➔ page 11
		3-3-3	Listening in	Activate/deactivate the function ➔ page 10
		3-3-4	Preselection	
			3-3-4-1 Presel. Number	Network provider dialling code, should be inserted **automatically** before the dialled phone number.
			3-3-4-2 With Preselect	First digits of the dialling codes, should be dialled **with** preselection.
			3-3-4-3 Without Presel	First digits of dialling codes, should be dialled **without** preselection.

4 Voice Mail

4-1	Set Key 1 **(all devices)**	4-1-1	Netw. Mailbx	Assign key **1** with network mailbox and enter the network mailbox number (in idle status, press and **hold** key **1** to dial). **Netw. Mailbx:** your network provider's answer machine; must be requested separately. The network mailbox list can be displayed if your network provider supports this function and if key **1** has been assigned with the network mailbox.
	(Devices with answer machine only)	4-1-2	Answer Mach.	Assign key **1** with answer machine (in idle status, press and **hold** to dial).
4-2	Answer Mach.	Activating/deactivating the answer machine		
4-3	Call Screening	4-3-1	Handset	You can use the loudspeaker on the handset to screen a message that is being recorded.
4-4	Announcements	4-4-1	Rec announce	➔ page 9
		4-4-2	Play announce	Play your announcement
		4-4-3	Del announce	Delete your announcement
4-5	Message Length	4-5-1	Maximum	Do not limit the recording time for each call.
		4-5-2	30 sec	Limit the recording time to 30 sec per call.
		4-5-3	60 sec	Limit the recording time to 60 sec per call.
		4-5-4	120 sec	Limit the recording time to 120 sec per call.
4-6	Ring Delay	4-6-1	Immediately	Call is answered immediately.
		4-6-2	10 sec	Call is answered after 10 seconds.
		4-6-3	20 sec	Call is answered after 20 seconds.
		4-6-4	30 sec	Call is answered after 30 seconds.
		4-6-5	Auto	If there are no new messages, the answer machine answers a call after **18 seconds**. If new messages are present, the answer machine answers a call after just **10 seconds**.

Version: 31.01.2011

A31008-M2005-Z701-1-7619

Issued by
Gigaset Communications GmbH
Frankenstr. 2a
D-46395 Bocholt

Manufactured by Gigaset Communications GmbH
under trademark license of Siemens AG.
As of 1 Oct. 2011 Gigaset products bearing the
trademark "Siemens" will exclusively use the
trademark "Gigaset".

© Gigaset Communications GmbH 2011
All rights reserved. Subject to availability.
Rights of modification reserved.
www.gigaset.com

This user guide is made from 100% recycled paper.